

DMX Control 192

This powerful little controller enables you to control most of Robe lighting products. The DMX Control 192 offers 192 DMX control channels; up to 12 projectors can be controlled; manual control of all projectors by joystick; fade-in time and step time adjustable via 2 faders.



Technical Specification

Electrical specification

- Wiring options: 115, 200-230 V AC, 50/60 Hz
- Wiring options: 115, 200-230 V AC, 50/60 Hz

Mechanical specification

- Height: 70 mm (2.7")
- Width: 176 mm (6.9")
- Length: 483 mm (19.01")
- Height: 70 mm (2.7")
- Width: 176 mm (6.9")
- Length: 483 mm (19.01")

Control and programming

- Number of control channels: 192
- Up to 12 projectors each of max. 16 channels can be individually controlled
- 40 freely-programmable programs with up to 99 steps each
- Number of control channels: 192
- Up to 12 projectors each of max. 16 channels can be individually controlled
- 40 freely-programmable programs with up to 99 steps each

Rigging

- 19" 4U rack mountable
- 19" 4U rack mountable